



Active holder for fixed installation

With tilt swivel. 2,7A charging. 12/24V. With Easy-switching system. Charging via pogo pins.

Item no: 713347

EAN Number: 7320287133479

An active holder which is to be connected inside the dashboard, this gives a discreet, neat installation without cables hanging over the interior! You can choose to use the holder as an active holder for charging of your device only, or to connect an adapter to the Molex connector for additional features. Then you can use the holder also for power supply of a GPS receiver or other own solutions (can not be used for data communication or audio connection). 12/24 Volt. The product is E-approved. Connect the power cable with a 2 A fuse. 2,7A charger. Professional installation recommended.

Easy-switching system:

The easy-switching system enables you to upgrade the holder only, and keep the installed cables. It saves you a lot of time! When upgrading to a new device, you do not longer need to make a full installation. Same goes for maintenance in case of warranty or damage. You simply disconnect the holder from the charging cable via the Molex 6-pin quick connector, and then connect the new holder. The switch is done in a few seconds.

The holder is equipped with a tilt swivel so you can easily adjust the angle for better viewing, or switch between portrait and landscape mode. Tilts 17° and swivels 360°. Mounting plate 42x50 mm with 4 mm AMPS-holes. Made of high grade black ABS/Acetal plastic. Made in Sweden. Connect the power cable with a 3A fuse. Professional installation recommended. Attach onto a ProClip Mounting Platform or a Pedestal Mount.

Fits the following models:

Zebra HC20
Zebra HC25
Zebra HC50
Zebra HC55
Zebra TC22
Zebra TC27

For a complete list, see

www.brodit.com/en/product/713347

Measurements:

Height 108 mm
Width 81 mm
Depth 65 mm
Volume 569 cm³
Weight 309 g

Charging specifications:

- Input voltage: 10-30VDC
- Charging voltage: 5.4V
- Output current (Typ): 2.7A
- Rated power: 15W
- Input & output protection: Input polarity reversal/Output over voltage/Output over current/Output shortprotection
- LED charging indicator: Power input indicator(Green), Ovp/Ocp/Output short (Red)
- DC-DC Conversion Efficiency: 88%
- Operating temperature: 0°C ~ +40°C
- Storage temperature: -20°C ~ +80°C
- Made of material: ABS+PC
- Approvals: CE, E-mark, FCC, RoHS