



**FRITZ!DECT 350**

**Technical specifications**



## **Technical specifications**

### **Features**

Magnetic door/window contact

LED shows standby, updates, registration

Immediately detects open doors and open/tilted windows	mode and successful registration
Helps save on heating costs when used together with FRITZ! radiator controls	Can be used with any FRITZ!Box with a DECT base station (FRITZ!OS 7.50 or later) via DECT ULE
Switches and controls all FRITZ! Smart Home devices and compatible Zigbee devices	Automatic update function for new features
Can be used in scenes, templates and routines	Easy to set up and optimized for use in the FRITZ!Box user interface
Check status in FRITZ!App Smart Home, FRITZ!Fon and FRITZ!OS	

## Installation

Can be mounted on almost all window and door frames	Can be mounted flexibly with the adhesive strips supplied
Can be mounted "invisibly" in standard window frames with Eurofold	

## Device properties

Dimensions of sensor (W x H x D): approx. 91 x 24 x 12 mm	Wireless standard: DECT ULE
Dimensions of magnet (W x H x D): approx. 28.5 x 15 x 6.5 mm	Frequency range: 1880 - 1900 MHz
	Radio range: up to 40 meters indoors

Weight of sensor:  
approx. 36 g  
(with batteries)

Weight of magnet:  
approx. 6 g

Battery operation: 2 x  
AAA batteries

Maximum transmitter  
power: 250 mW

Operational at an  
ambient temperature of  
0°C to 50°C (not in wet  
or damp rooms)

## **Package contents**

FRITZ!DECT 350

Quick Guide

2 x AAA batteries

Adhesive strips for test  
mounting

Adhesive strips for  
permanent installation

Pin tool for resetting

## **Requirements**

FRITZ!Box with DECT  
base station and  
FRITZ!OS 7.50 or later

## **Article number**

20003050