



## FRITZ!Repeater 3000 AX

### Features

A high-performance repeater for wide coverage and high data throughput for multiple

Two gigabit LAN ports:  
Connected devices  
(computers, printers,  
audio/video players,

devices in Wi-Fi networks

With Mesh Wi-Fi you can combine several wireless access points into one intelligent system (FRITZ!OS 6.90 or later)

Three wireless radio units: 2400 Mbit/s + 1200 Mbit/s (5 GHz) + 600 Mbit/s (2.4 GHz) for the optimal supply of multiple wireless devices (Wi-Fi 6)

Supports 160 MHz Wi-Fi connections (VHT160)

etc.) are granted Wi-Fi functionality can also be connected to a router via network cable (LAN bridge)

Secure upon delivery with WPA2 encryption, WPA3/2 transition mode also available

Compatible with all common wireless routers

Simple, secure configuration at the touch of a button (WPS)

Display shows connection quality and status

Supports the IPv6 internet protocol

## Ports and interfaces

Wireless access point: compatible with all wireless routers with the 802.11 ax/ac/n/g/a Wi-Fi standards

Wi-Fi: 2400 Mbit/s (5 GHz, 4 x 4) + 1200 Mbit/s (5 GHz, 2 x 2) + 600 Mbit/s (2.4 GHz, 2 x 2)

2 x gigabit ports (10/100/1000 Mbit/s)

Connection to mains with power adapter provided (230 V, 50 Hz)

## Simple setup

Optimized for use with all FRITZ!Box models

Easy operation via browser-based user

Installation at the touch  
of a button with Wi-Fi  
Protected Setup (WPS)

interface  
(<http://fritz.repeater>)

## **Package contents**

FRITZ!Repeater 3000  
AX  
Power supply unit

Network cable  
Quick guide

## **Device properties**

Measurements (W x H x  
D): approx. 9 x 19 x  
14.5 cm

Average power  
consumption: ca. 11 W

## **Article number**

20002988