# i-SENSYS MF630 Series

# COMPLETE LASER PRINTING SOLUTIONS FOR SMALL BUSINESSES: SIMPLE OPERATION, HIGH-PERFORMANCE.

High-quality colour laser printing from an efficient and low maintenance multifunction unit: the MF630 series has been built to meet the demands of modern small businesses.

MF631Cn

MF633Cdw

MF635Cx

## Touchscreen simplicity

The MF630 series' intuitive 12.7 cm colour touchscreen allows users to easily access the features they need. From straightforward tasks through to more complex commands, the keyless touchscreen operation allows any job to be executed quickly; improving productivity and removing the need for training or technical support. And as the user interface can be customised on the MF635Cx, the printer can be adapted to fit seamlessly into any business.

## Time-saving apps

Time is a luxury that many small businesses don't have. The MF635Cx features an Application Library packed full of innovations to save time and increase user efficiency. The system allows frequently used forms, templates and flyers to be produced with a single tap, without the need to connect additional devices. Other useful features include an eco-copy mode, which condenses eight pages onto one A4 sheet, and an ID card copy function to capture both sides of passports or driving licenses onto a single page.

## Designed for mobile business

Modern small businesses are agile, dispersed, and mobile. The MF630 series has been engineered for the workforce of today, with support for Airprint (Apple) and Mopria (Android) as well as NFC and QR-code pairing, for quick, frictionless connectivity. The Wireless Direct connection also allows guests to print without requiring network access, while the Canon PRINT business app unlocks a range of invaluable features designed to enhance mobile working.

## Print and scan in seconds

Productivity matters: small businesses need a reliable printer that doesn't compromise on efficiency. The MF630 series prints at 18 pages per minute, ensuring it can keep pace with even the most fast-paced of small businesses. In addition, single-pass double-sided scanning on the MF635Cx further speeds up workflows, saving invaluable time and helping staff to increase their output.

## Captivating colour quality

Harnessing all of Canon's renowned laser quality, the MF630 range delivers a bold, punchy colour output that commands attention. In addition to the rapid print rate and efficient operation, the series offers uncompromisingly vibrant image reproduction, which ensures staff can maximise the impact of their sales, marketing or internal communication materials.

## Minimising maintenance

With its all-in-one cartridge and auto toner seal removal system, the MF630 series reduces maintenance demands, and gives small businesses back the time to do what they do best. Along with simpler installation, higher-yield cartridges are also available, and the MF630 series' consumable status monitor alerts users to any upcoming replacements required, helping to alleviate upkeep frustrations.

## Canon

**Print Management made easy**

Universal Login Manager (ULM) is designed to protect and optimise your device by providing simple, yet secure, user authentication options for device access control. ULM allows for print permissions to be established for users and delivers personalised workflows to drive productivity. In addition, simple reporting tools provide a powerful business insight into device and user activity and costs. Included with MF635Cx. Activation is required.

## OPTIONAL ACCESSORIES

**Barcode Print Kit- E1 (Available on MF635Cx)**

• Installs bar code fonts for bar code printing. This kit, which is delivered boxed, includes a license access certificate for activation.

**Barcode Print Kit- E1E (Available on MF635Cx)**

• Installs bar code fonts for bar code printing. This kit, which is delivered electronically, includes a license access certificate for activation.

**Send PDF Security Feature Set-E1 (Available on MF635Cx)**

• Send encrypted PDF and add digital device signature to PDF files. This kit, which is delivered electronically, includes a license access certificate for activation.

**Telephone 6 Kit (Available on MF635Cx)**

• Optional telephone handset for fax function.

### i-SENSYS MF635Cx

# TECHNICAL SPECIFICATIONS

# i-SENSYS MF630 Series

| | | | |
|---|---|---|---|
| **Machine type** | Colour Laser All-In-One | **Max. scan width** | 216mm |
| **Available functions** | i-SENSYS MF631Cn/i-SENSYS MF633CDW:<br>Print, Copy and Scan | **Scan to E-mail** | i-SENSYS MF631Cn/i-SENSYS MF633Cdw:<br>TIFF, JPEG, PDF, Compact PDF, Searchable PDF |
| | i-SENSYS MF635Cx:<br>Print, Copy, Scan and Fax | | i-SENSYS MF635Cx:<br>TIFF, JPEG, PDF, Compact PDF, Searchable PDF,<br>Encrypted PDF/PDF (Digital signature)* |
| **PRINTER** | | | *Accessory - Send PDF Security Feature Set-E1 is required |
| **Print speed** | i-SENSYS MF631Cn:<br>Single sided: Up to 18 ppm (A4)<br>　　　　　　Up to 32 ppm (A5-Landscape) | **Scan to PC** | i-SENSYS MF631Cn/i-SENSYS MF633Cdw:<br>TIFF, JPEG, PDF, Compact PDF, Searchable PDF |
| | i-SENSYS MF633Cdw/i-SENSYS MF635Cx:<br>Single sided : Up to 18 ppm (A4)<br>　　　　　　Up to 32 ppm(A5-Landscape) | | i-SENSYS MF635Cx:<br>TIFF, JPEG, PDF, Compact PDF, Searchable PDF,<br>Encrypted PDF/PDF (Digital signature)* |
| | Double sided : Up to 11 ipm (A4) | | *Accessory - Send PDF Security Feature Set-E1 is required |
| **Printing method** | Colour laser beam printing | **Scan to USB memory key** | i-SENSYS MF631Cn/i-SENSYS MF633Cdw:<br>TIFF, JPEG, PDF, Compact PDF, Searchable PDF |
| **Print quality** | Up to 1200 x 1200 dpi | | i-SENSYS MF635Cx:<br>TIFF, JPEG, PDF, Compact PDF, Searchable PDF,<br>Encrypted PDF/PDF (Digital signature)* |
| **Print resolution** | 600 x 600 dpi | | |
| **Warm-up time** | Approx. 13 seconds or less from power on | | *Accessory - Send PDF Security Feature Set-E1 is required |
| **First Print Out Time** | Colour approx.: 12 seconds or less<br>Mono approx.: 10.9 seconds or less | **Scan to FTP** | i-SENSYS MF631Cn/i-SENSYS MF633Cdw:<br>TIFF, JPEG, PDF, Compact PDF, Searchable PDF |
| **Printer languages** | i-SENSYS MF631Cn:<br>UFRII | | i-SENSYS MF635Cx:<br>TIFF, JPEG, PDF, Compact PDF, Searchable PDF,<br>Encrypted PDF/PDF (Digital signature)* |
| | i-SENSYS MF633Cdw:<br>UFRII, PCL5c*, PCL6 | | *Accessory - Send PDF Security Feature Set-E1 is required |
| | i-SENSYS MF635Cx:<br>UFRII, PCL 5c*, PCL6, Adobe® PostScript | **Scan to Cloud** | TIFF/JPEG/PDF/PNG* |
| | *Commands supported only. Third party driver or direct printing from<br>application required. | | *Scan by MF Scan Utility or Canon PRINT Business |
| **Fonts** | i-SENSYS MF633Cdw:<br>45 PCL fonts | **iFAX** | i-SENSYS MF635Cx:<br>ITU-T.37 |
| | i-SENSYS MF635Cx:<br>93 PCL fonts<br>136 PostScript fonts | **FAX** | |
| | | **Modem speed** | i-SENSYS MF635Cx:<br>33.6 Kbps (Up to 3 seconds/page)* |
| **Print margins** | 5 mm-top, bottom, left and right<br>10 mm-top, bottom, left and right (Envelope) | | *Based on ITU-T Standard Chart No. 1 |
| **Toner saver mode** | Yes | **Receive mode** | i-SENSYS MF635Cx:<br>Fax only, Fax/Tel Auto Switch, Answer Mode, Manual |
| **Advanced printing features** | i-SENSYS MF631Cn/i-SENSYS MF633Cdw:<br>Secure Print<br>Print from USB memory key (JPEG/TIFF/PDF)<br>Google Cloud Print Ready<br>iOS: AirPrint, Canon PRINT Business app<br>Android; Mopria certified, Canon Print Service Plug-in,<br>Canon PRINT Business app | **Fax resolution** | i-SENSYS MF635Cx:<br>Standard: 200 x 100 dpi<br>Fine: 200 x 200 dpi<br>Super fine: 200 x 400 dpi<br>Ultra fine: 400 x 400 dpi |
| | i-SENSYS MF635Cx:<br>Secure Print<br>Print from USB memory key (JPEG/TIFF/PDF)<br>Barcode Print*<br>Google Cloud Print Ready<br>iOS: AirPrint, Canon PRINT Business app<br>Android; Mopria certified, Canon Print Service Plug-in,<br>Canon PRINT Business app | **FAX memory** | i-SENSYS MF635Cx:<br>Up to 512 pages* |
| | | | *Based on ITU-T Standard Chart No. 1 |
| | | **Speed dials** | i-SENSYS MF635Cx:<br>Up to 281dials |
| | *Accessory - Barcode Printing Kit-E1 or Barcode Printing Kit-E1E - is<br>required | **Group dials/destinations** | i-SENSYS MF635Cx:<br>Max. 199 dials / Max. 199 destinations |
| **COPIER** | | **Sequential broadcast** | i-SENSYS MF635Cx:<br>Max. 310 destinations |
| **Copy speed** | i-SENSYS MF631Cn/i-SENSYS MF633Cdw:<br>Single sided (A4): Up to 18 ppm | **Memory backup** | i-SENSYS MF635Cx:<br>Permanent fax memory backup (Backup with flash<br>memory) |
| | i-SENSYS MF635Cx:<br>Single sided (A4): Up to 18 ppm<br>Double sided (A4): Up to 11 ipm | **Double sided faxing** | i-SENSYS MF635Cx:<br>Yes (Transmit and Receive) |
| **First Copy Output Time<br>(FCOT)** | i-SENSYS MF631Cn:<br>Platen (A4):<br>Colour Approx. 14.0 seconds or less<br>Mono Approx. 12.0 seconds or less | **Other features** | i-SENSYS MF635Cx:<br>Fax Forwarding, Dual Access, Remote Reception, PC Fax<br>(TX only) DRPD, ECM, Auto Redial, Fax Activity Reports, Fax<br>Activity Result Reports, Fax Activity Management Reports |
| | i-SENSYS MF633Cdw/i-SENSYS MF635Cx:<br>ADF (A4):<br>Colour Approx. 14.2 seconds or less<br>Mono Approx. 12.4 seconds or less<br>Platen (A4):<br>Colour Approx. 14.0 seconds or less<br>Mono Approx. 12.0 seconds or less | **MEDIA HANDLING** | |
| | | **Scanner type** | i-SENSYS MF631Cn:<br>Platen |
| | | | i-SENSYS MF633Cdw:<br>Platen, ADF |
| **Copy resolution** | Up to 600 x 600 dpi | | i-SENSYS MF635Cx:<br>Platen, 2-sided ADF (single pass) |
| **Copy modes** | Text/Photo/Map (Default),Text/Photo/Map (quality),<br>Printed Image, Text | **Paper input (Standard)** | i-SENSYS MF631Cn:<br>150-sheet cassette<br>1-sheet manual feed slot |
| **Double sided copying** | i-SENSYS MF631Cn/i-SENSYS MF633Cdw:<br>1-sided to 2-sided (Automatic) | | i-SENSYS MF633Cdw/i-SENSYS MF635Cx:<br>150-sheet cassette<br>1-sheet manual feed slot<br>50-sheet ADF |
| | i-SENSYS MF635Cx:<br>2-sided to 2-sided (Automatic) | **Paper output** | 100-sheet |
| **Multiple copy** | Up to 999 copies | **Media types** | Plain paper, Recycled paper, Heavy Paper, Colour paper,<br>Glossy paper, Label, Post card, Envelope |
| **Reduction / Enlargement** | 25-400% in 1% increments | **Media sizes** | i-SENSYS MF631Cn:<br>Cassette :<br>A4, A5, A5 (Landscape), B5, Legal, Letter, Executive,<br>Statement, OFFICIO, B-OFFICIO, M-OFFICIO, GLTR, GLGL,<br>Foolscap, 16K, Post card, Indexcard, Envelop (COM10, DL,<br>C5, Monarch),<br>Custom sizes: Min. 76.2 x 127 mm  Max. 215.9 x 355.6 mm. |
| **Other features** | Frame Erase, Collate, 2 on 1, 4 on 1, ID card copy | | |
| **SCANNER** | | | |
| **Type** | Colour | | Manual feed slot:<br>A4, A5, A5 (Landscape), B5, Legal, Letter, Executive,<br>Statement, OFFICIO, B-OFFICIO, M-OFFICIO, GLTR, GLGL,<br>Foolscap, 16K, Post card, Indexcard, Envelope (COM10, DL,<br>C5, Monarch),<br>Custom sizes: Min 76.2 x 127 mm  Max. 215.9 x 355.6 mm. |
| **Scan resolution** | Optical: Up to 600 x 600 dpi<br>Enhanced: Up to 9600 x 9600 dpi | | |
| **Scan speed** | i-SENSYS MF631Cn/i-SENSYS MF633Cdw:<br>Single sided mono: 27ipm (300x600dpi)<br>Single sided colour: 14ipm (300x600dpi) | | i-SENSYS MF633Cdw/i-SENSYS MF635Cx:<br>Cassette :<br>A4, A5, A5 (Landscape), B5, Legal, Letter, Executive,<br>Statement, OFFICIO, B-OFFICIO, M-OFFICIO, GLTR, GLGL,<br>Foolscap, 16K, Post card, Indexcard, Envelop (COM10, DL,<br>C5, Monarch),<br>Custom sizes: Min. 76.2 x 127 mm  Max. 215.9 x 355.6 mm. |
| | i-SENSYS MF635Cx:<br>Single sided mono: 27ipm (300x600dpi)<br>Single sided colour: 14ipm (300x600dpi)<br>Double sided mono: 47ipm (300x600dpi)<br>Double sided colour: 27ipm (300x600dpi) | | |
| **Colour scanning depth** | 24 bit/24 bit (input/output) | | |
| **Greyscales** | 256 levels | | |
| **Compatibility** | TWAIN , WIA, ICA | | |

# TECHNICAL SPECIFICATIONS

# i-SENSYS MF630 Series

| | | | |
|---|---|---|---|
| **Media weights** | Manual feed slot:<br>A4, A5, A5 (Landscape), B5, Legal, Letter, Executive, Statement, OFFICIO, B-OFFICIO, M-OFFICIO, GLTR, GLGL, Foolscap, 16K, Post card, Indexcard, Envelope (COM10, DL, C5, Monarch),<br>Custom sizes: Min 76.2 x 127 mm  Max. 215.9 x 355.6 mm.<br><br>ADF:<br>A4, A5, B5, Legal, Letter, Statement,<br>Custom sizes: Min. 128 x 139.7 mm Max 215.9 x 355.6 mm<br>i-SENSYS MF631Cn:<br>Cassette: 52 to 163 g/m² (Up to 200 g/m² with Glossy paper)<br>Manual feed slot: 52 to 163 g/m² (Up to 200 g/m² with Glossy paper)<br><br>i-SENSYS MF633Cdw/i-SENSYS MF635Cx:<br>Cassette: 52 to 163 g/m² (Up to 200 g/m² with Glossy paper)<br>Manual feed slot: 52 to 163 g/m² (Up to 200 g/m² with Glossy paper)<br>ADF: 50 to 105 g/m² | | **i-SENSYS MF635Cx:**<br>Presto! Page Manager,<br>MF Scan Utility,<br>Remote User Interface (RUI),<br>Department ID Management,<br>Toner Status Tool,<br>iW Management Console: Server-based software for centralised management of a fleet of devices<br>eMaintenance: embedded RDS allows remote eMaintenance services such as meter capture, automatic consumables management and remote diagnostics.<br>uniFLOW Compatibility with embedded uniFLOW Login Device Client<br>Universal Login Manager |
| **Double sided printing** | i-SENSYS MF633Cdw/i-SENSYS MF635Cx:Automatic<br>Cassette:<br>A4, B5, Legal, Letter, Executive, OFFICIO, B-OFFICIO, M-OFFICIO, GLTR, GLGL, Foolscap, 16K<br>Custom size - Min. 182 x 257 mm Max. 215.9 x 355.6 mm<br>60 to 120 g/m² | | |

**INTERFACE & SOFTWARE**

| | |
|---|---|
| **GENERAL FEATURES** | |
| **Recommended Monthly Print Volume** | 250 - 2,500 pages per month |
| **Duty cycle** | Max. 30,000 pages per month*<br><br>*Duty cycle is defined as the maximum number of printed pages for a single peak month. Any usage above the recommended duty cycle may decrease the life of the product |

| | | | |
|---|---|---|---|
| **Interface type** | i-SENSYS MF631Cn:<br>USB 2.0 Hi-Speed, 10BASE-T/100BASE-TX/1000Base-T<br><br>i-SENSYS MF633Cdw/i-SENSYS MF635Cx:<br>USB 2.0 Hi-Speed, 10BASE-T/100BASE-TX/1000Base-T, Wireless 802.11b/g/n, Wireless Direct Connection | **Processor Speed** | 800MHz x 2 |
| | | **Memory** | 1GB |
| | | **Control panel** | 12.7 cm LCD Colour Touch Screen |
| **Operating System compatibility** | Windows® 10 / Windows® 8.1 / Windows® 7 / Server® 2016 / Server® 2012R2 / Server® 2012 / Server® 2008R2 / Server® 2008<br>Mac OS X version 10.7.5 & up<br>Linux*/Citrix<br><br>*Web distribution only. Linux support printing only. | **Dimensions with trays (W x D x H)** | i-SENSYS MF631Cn:<br>451 mm x 460 mm x 347 mm<br><br>i-SENSYS MF633Cdw/i-SENSYS MF635Cx:<br>451 mm x 460 mm x 400 mm |
| **Network Protocol** | i-SENSYS MF631Cn:<br>Print:<br>LPD, RAW, WSD-Print (IPv4,IPv6)<br>Scan:<br>Email, SMB, WSD-Scan(IPv4, IPv6), FTP-Scan<br>TCP/IP Application Services:<br>Bonjour(mDNS), HTTP, HTTPS, POP before SMTP (IPv4,IPv6)<br>DHCP, ARP+PING, Auto IP, WINS (IPv4)<br>DHCPv6 (IPv6)<br>Management:<br>SNMPv1, SNMPv3 (IPv4,IPv6)<br>Security:<br>IP/Mac address filtering, IEEE802.1X, SNMPv3, SSL (HTTPS, IPPS)<br><br>i-SENSYS MF633Cdw:<br>Print:<br>LPD, RAW, WSD-Print (IPv4,IPv6)<br>Scan:<br>Email, SMB, WSD-Scan(IPv4, IPv6), FTP-Scan<br>TCP/IP Application Services:<br>Bonjour(mDNS), HTTP, HTTPS, POP before SMTP (IPv4,IPv6)<br>DHCP, ARP+PING, Auto IP, WINS (IPv4)<br>DHCPv6 (IPv6)<br>Management:<br>SNMPv1, SNMPv3 (IPv4,IPv6)<br>Security (wired):<br>IP/Mac address filtering, IEEE802.1X, SNMPv3, SSL (HTTPS, IPPS)<br>Security (wireless):<br>WEP (64/128 bit), WPA-PSK (TKIP/AES), WPA2-PSK (AES)<br><br>i-SENSYS MF635Cx:<br>Print:<br>LPD, RAW, WSD-Print (IPv4,IPv6)<br>Scan:<br>Email, SMB, WSD-Scan(IPv4, IPv6), FTP-Scan<br>TCP/IP Application Services:<br>Bonjour(mDNS), HTTP, HTTPS, POP before SMTP (IPv4,IPv6)<br>DHCP, ARP+PING, Auto IP, WINS (IPv4)<br>DHCPv6 (IPv6)<br>Management:<br>SNMPv1, SNMPv3 (IPv4,IPv6)<br>Security (wired):<br>IP/Mac address filtering, IEEE802.1X, SNMPv3, SSL (HTTPS, IPPS)<br>Security (wireless):<br>WEP (64/128 bit), WPA-PSK (TKIP/AES), WPA2-PSK (AES) | **Installation space (W x D x H)** | i-SENSYS MF631Cn:<br>651 mm x 1,211 mm x 667.4 mm<br><br>i-SENSYS MF633Cdw/i-SENSYS MF635Cx:<br>651 mm x 1,211 mm x 776 mm |
| | | **Weight** | i-SENSYS MF631Cn:<br>Approx. 19.5 Kg<br><br>i-SENSYS MF633Cdw/i-SENSYS MF635Cx:<br>Approx. 22 Kg |
| | | **Operating environment** | Temperature: 10 to 30ºC (50 to 86ºF)<br>Humidity: 20 to 80% RH (no condensation) |
| | | **Power Source** | 220-240V(±10%)  50/60Hz (±2Hz) |
| | | **Power Consumption** | i-SENSYS MF631Cn:<br>Maximum: Approx. 850 W<br>Standby: Approx. 13.6 W<br>Sleep mode: Approx. 0.94 W<br>Typical Electricity Consumption (TEC): 0.5 kWh/week (230V)<br>For detailed information relating to Lot26 regulation, please go to:  http://www.canon-europe.com/For_Work/Lot26/index.aspx<br><br>i-SENSYS MF633Cdw/i-SENSYS MF635Cx:<br>Maximum: Approx. 850 W<br>Standby: Approx. 13.6 W<br>Sleep mode: Approx. 0.94 W*<br>Typical Electricity Consumption (TEC): 0.5 kWh/week (230V)<br>For detailed information relating to Lot26 regulation, please go to:  http://www.canon-europe.com/For_Work/Lot26/index.aspx<br><br>*When in wireless mode, consumption will be 0.98W |
| | | **Noise Levels** | Sound Pressure* :<br>Active: 49 dB<br>Standby: Inaudible<br><br>Sound Power*:<br>Active: 64dB or less<br>Standby: Inaudible<br><br>*Declared noise emission in accordance with ISO 9296 |
| | | **CONSUMABLES** | |
| | | **Cartridges** | Cartridge 045 Black (1,400 pages *)**<br>Cartridge 045H Black (2,800 pages *)**<br>Cartridge 045 Cyan (1,300 pages *)**<br>Cartridge 045H Cyan (2,200 pages *)**<br>Cartridge 045 Magenta (1,300 pages *)**<br>Cartridge 045H Magenta (2,200 pages *)**<br>Cartridge 045 Yellow (1,300 pages *)**<br>Cartridge 045H Yellow (2,200 pages *)**<br><br>*Based on ISO/IEC 19798<br>**Printer ships with Black: 1,400 pages, C/M/Y: 690 pages starter cartridges |
| | | **Accessories/ options** | |
| **Software and printer management** | i-SENSYS MF631Cn/i-SENSYS MF633Cdw:<br>Presto! Page Manager,<br>MF Scan Utility,<br>Remote User Interface (RUI),<br>Department ID Management,<br>Toner Status Tool,<br>iW Management Console: Server-based software for centralised management of a fleet of devices<br>eMaintenance: embedded RDS allows remote eMaintenance services such as meter capture, automatic consumables management and remote diagnostics. | **Items** | i-SENSYS MF635Cx:<br>TEL 6 Kit Long Cord (Telephone handset)<br>Barcode Printing Kit-E1<br>Barcode Printing Kit-E1E<br>MiCard Multi (Card reader for identification with RFID or magnetic cards with uniFLOW)<br>Micard Plus (Card reader for identification with RFID or magnetic cards with uniFLOW)<br>MiCard Attachment Kit-B1<br>Send PDF Security Feature Set-E1 |

Canon

# COMPLETE LASER PRINTING SOLUTIONS FOR SMALL BUSINESSES: SIMPLE OPERATION, HIGH-PERFORMANCE.

# i-SENSYS MF630 Series

High-quality colour laser printing from an efficient and low maintenance multifunction unit: the MF630 series has been built to meet the demands of modern small businesses.

**PRODUCT DETAILS:**

| PRODUCT NAME | MERCURY CODE | EAN CODE |
|---|---|---|
| i-SENSYS MF635Cx | 1475C001AA | 4549292068368 |
| i-SENSYS MF633Cdw | 1475C007AA | 4549292068436 |
| i-SENSYS MF631Cn | 1475C017AA | 4549292068535 |

**OPTIONAL ACCESSORIES:**

| PRODUCT NAME | MERCURY CODE | EAN CODE |
|---|---|---|
| Barcode Printing Kit-E1 | 5143B001AA | 4960999689951 |
| Barcode Printing Kit-E1E | 5143B002AA | - |
| Send PDF Security Feature Set-E1 | 9594B002AA | - |
| Telephone 6 Kit EU (CW) | 0752A054AA | 4960999453910 |

**CONSUMABLES:**

| PRODUCT NAME | MERCURY CODE | EAN CODE |
|---|---|---|
| Cartridge 045 Black | 1242C002AA | 4549292073669 |
| Cartridge 045 H Black | 1246C002AA | 4549292073782 |
| Cartridge 045 Yellow | 1239C002AA | 4549292073577 |
| Cartridge 045 H Yellow | 1243C002AA | 4549292073690 |
| Cartridge 045 Magenta | 1240C002AA | 4549292073607 |
| Cartridge 045 H Magenta | 1244C002AA | 4549292073720 |
| Cartridge 045 Cyan | 1241C002AA | 4549292073638 |
| Cartridge 045 H Cyan | 1245C002AA | 4549292073751 |

**EASY SERVICE PLAN:**

| ITEM NAME | MERCURY CODE | EAN CODE |
|---|---|---|
| Installation service | 7950A546AA | 4960999794426 |
| 3-year on-site next day service-Pack B | 7950A526AA | 4960999793306 |

**MEASUREMENT / LOGISTIC INFORMATION:**

| Product Name | Mercury code | Package Style | Quantity per pack | Length (mm) | Width (mm) | Height (mm) | Weight (kg) |
|---|---|---|---|---|---|---|---|
| i-SENSYS MF635Cx | 1475C001AA | Box | 1 | 586 | 569 | 523 | 29 |
| i-SENSYS MF633Cdw | 1475C007AA | Pallet | 8 | 1190 | 1150 | 1056 | - |
| | | Container 40ft HC | 320 | - | - | - | - |
| i-SENSYS MF631Cn | 1475C017AA | Box | 1 | 586 | 569 | 475 | 26 |
| | | Pallet | 8 | 1190 | 1150 | 950 | - |
| | | Container 40ft HC | 320 | - | - | - | - |

## WHAT'S IN THE BOX?

- Main unit
- Cartridge 045 Black (1,400 pages)
- Cartridge 045 Cyan/Magenta/ Yellow starter (690 pages)
- Power supply cable
- Telephone cable
- Starter Guide
- User software DVD-ROM
- Warranty card

**Canon**