

## Lenovo Go Wireless Multi-Device Mouse

Designed to be the only mouse you need, the **Lenovo Go Wireless Multi-Device Mouse** can be paired with up to 3 devices and effortlessly cycle between them with a push of a button. Beyond its multi-tasking capabilities, this productivity-powerhouse can be used on nearly any surface and rarely runs out of battery, thanks to its blue optical sensor and wireless Qi or wired USB-C fast-chargeable battery.

Lenovo  
Go



# Three Devices, One Mouse



Lenovo

# Lenovo Go Wireless Multi-Device Mouse



## WHY CHOOSE THE LENOVO GO WIRELESS MULTI-DEVICE MOUSE?



### Multi-Pairing, Multi-Surface

The Lenovo Go Wireless Multi-Device Mouse supports pairing up to 3 devices using USB-C and Bluetooth® with a quick switch button. Beyond 3-device pairing, you'll also enjoy the ability to use a Lenovo Unified Pairing Receiver to connect other devices with one dongle. Plus, its blue optical sensor ensures you experience maximum precision on almost every surface.



### Multi-Task, Multi-Location

Crafted as an all-in-one solution, this mouse features on-the-fly adjustable DPI sensitivity, a programmable utility button with shortcuts configured for TEAMS meetings by default, and is portable enough to take with you anywhere.



### Multi-Option, Fast-Charging

With a fast-chargeable battery that provides 2 months of use on a single 1.5-hour charge<sup>1</sup> and supports both wired USB-C and wireless Qi charging, the Lenovo Go Wireless Multi-Device Mouse is hard to beat.

## SPECIFICATIONS

### PERFORMANCE

<b>Battery<sup>1</sup></b>	
<b>Capacity</b>	: 380 mAh
<b>Battery Life</b>	: Up to 2-3 Months in Single Charge
<b>Full Charge Time</b>	: 1.5 Hour (or less)
<b>Quick Charge</b>	: 15 minutes Charge, 1 Week Battery
<b>Charging Port</b>	: USB-C Charging
<b>Charging Cable</b>	: USB-C to USB-C, 0.5 m
<b>Wireless Charging</b>	: Qi

### Call Mode Function\*

Open/Show Teams App (Default)  
Volume Up (Default)  
Volume Down (Default)  
Mute/Unmute Teams (Default)  
Mute/Unmute Microphone  
Mute/Unmute Speaker  
Answer Voice Call (Default)  
End Voice Call (Default)  
Share Screen  
Answer Call with Video  
Start/End Presentation  
Activate Virtual Pointer for PowerPoint

### DESIGN

<b>Dimensions (W x D x H) Mouse</b>	
<b>mm</b>	: 100 x 62 x 34
<b>inches</b>	: 3.95" x 2.43" x 1.35"
<b>Receiver</b>	
<b>mm</b>	: 18 x 15 x 9
<b>inches</b>	: 3.95" x 2.43" x 1.35"
<b>Sensor</b>	Blue Optical Sensor
<b>DPI</b>	On-the-fly Adjustable (2400, 1600, 800)
<b>Scrolling</b>	2-way Scroll Wheel (up/down)
<b>Number of Buttons</b>	3 (left click, right click, scroll click)
<b>IC Used</b>	Nordic IC (52810)

### CONNECTIVITY

<b>Type</b>	2.4 GHz Wireless
<b>Bluetooth®</b>	Bluetooth® 5.0
<b>Quick Pairing</b>	Swift Pair
<b>Dongle</b>	Nano USB-C Receiver
<b>Universal Pairing</b>	Supports Lenovo Universal Pairing

### INFORMATION

<b>Compatibility</b>	Windows, Chrome
<b>Software – Lenovo Accessory Central</b>	Manage Configurations of the Product
<b>Support OS</b>	- Windows
<b>Support</b>	2.4G connection only at launch
<b>Warranty</b>	1 Year
<b>Part Number (PN)</b>	
<b>Consumer (Storm Grey color)</b>	GY51C21211
<b>Commercial (Thunder Black color)</b>	4Y51C21217
<b>Ship Group (What's in the Box)</b>	Lenovo Go Wireless Multi-Device Mouse Lenovo USB-C Unified Pairing Receiver USB-C to USB-C Charging Cable Product and Warranty Information Document

<sup>1</sup> Battery life may vary based on usage.

<sup>2</sup> Need to install Lenovo Accessories Central.



ACCESSORYSMARTFIND.LENOVO.COM