



Compact, Portable Document Scanner

ADS-1300



www.brother.eu

Compact, Portable Document Scanner

Make everyday document scanning simple with the ADS-1300 compact, portable document scanner.

Scan and save your paper documents wherever you are working. Whether its utility bill, business documents or medical forms, once plugged into your laptop, you can scan and securely store data digitally and have instant access whenever you need it.

ADS-1300



Key features:

- Scan up to 30ppm
- 60ipm, 2-sided colour scan
- 20 Sheet Automatic Document Feeder (ADF)
- Power directly via USB Type-C
- Control up to 3 scan activity shortcuts direct from the device
- Dedicated plastic ID card slot
- Scan to PC³, Cloud^{3,}, USB Host
- PDF editing software included
- Optional paper output tray available

Scanning on the move

Designed with flexibility in mind, easily scan and save your paper documents whilst you are out of the office. Once plugged into your laptop, you can use the ADS-1300 to scan documents when it is most convenient for you.

High performance, every time

No matter where you scan from, you will get the same high performance, every time. With scan speeds of up to 60 sides per minute (2-sided), documents are saved quickly and effortlessly to PDF, File, Email and USB Host.

Versatile media handling

The time-saving 20 sheet Automatic Document Feeder (ADF) manages various sizes and thicknesses of paper (up to 128gsm) with ease. Whilst the dedicated card slot comfortably handles plastic ID cards.

Industry-leading software

Available as standard, Power PDF provides you with the flexibility to easily convert, edit and share documents in seconds.

Together with Kofax PaperPort, a document management solution, workflows can be created so that you can share, search and organise documents with ease and accuracy.



Product Form Factor Sheet Fed Portable Desktop Document Scanner

Technology Dual CIS (contact Image Sensor), LED Array Light Source **Control Panel** LED, Keys

Backup Clock Up to 24 hours

Local Interface

USB Type-C 3.2 Gen1, USB 2.0 Host (Rear) Up to 128GB

Configurable Shortcuts 3

Scan

Scan Speed (A4) Colour and Mono (300dpi) Up to 30ppm (pages per minute) (USB bus powered)¹⁰

Scan Speed 2-Sided (A4) Colour and Mono (300dpi) Up to 60ipm (images per minute) (30 sheets per minute) (USB bus powered)¹⁰ Resolution Optical Up to 600 x 600dpi (dots per inch)

Interpolated³ Up to 1,200 x 1,200dpi (dots per inch)

Wake-up Time USB 1.0sec

Colour Depth

48 bit colour processing (Input) 24 bit colour processing (Output)

Grey Scale 256 levels (8 bit)

Scanner Functions

Machine Functions File Format Support Including (Standard)PDF, PDF/A-1b), JPEG, TIFF

Direct Scan Yes⁹

Destinations³

Scan to PC (Image), Workflow, SharePoint (On Premise), Cloud

Feed Control

ADF Automatic Pop Up Edge Guide, Card Slot (Portrait) Separation Switch, Resume Scan³

Configurable Shortcuts

Create up to 3 preset scan to profiles using Brother iPrint&Scan for Desktop

Image Processing³ Advanced Features

Auto Deskew(Feed)9, Detect End of Page⁵, Margin Setting⁵, Auto Image Rotation⁵, Edge Fill⁵, Tear Fill⁵, Punch Hole Removal⁵. Auto Colour Detect Adjust9, Blank Page Removal⁹, Diffusion Adjustment - Grey, Colour Tone Adjustment, Background Processing⁵, Colour Drop⁵, Edge Emphasis⁵, Moire Reduction⁵, Vertical Streak Reduction⁵, B&W Threshold Adjustment⁵, Character Correction, B&W Inversion, Noise Reduction, Remove Ruled Line, 2in1 Scan, 1to2 Scan, Carrier Sheet Mode, Plastic Card Mode, Single Page Scan⁵, Continuous Scan⁵, Barcode Detection⁵, JPEG Compression⁵, Digital Imprinter⁵, Custom TWAIN Profiles⁵

Windows Drivers TWAIN | WIA Windows® 10, 11

Software for Windows

Desktop, Kofax PaperPort 14SE

with OCR, Kofax Power PDF

Standard v5, Remote Setup

Brother iPrint&Scan for

Macintosh Drivers ICA macOS 11x, 12.x, 13.x

Software for macOS

Brother iPrint&Scan for Desktop, Kofax Power PDF Standard v3, Remote Setup Linux Drivers

Easy Setup¹²

Simplifying the install process with easy access to the right drivers and software for the installation of your Brother machine for your PC

Visit support.brother.com for a full list of supported OS and to download the latest drivers and software

Media Handling

Media Input / Output ADF Up to 20 sheets⁴

Media Sizes Multiple Pages⁸ Width 51 - 215.9mm, Height 70 - 355.6mm

Media Type ADF

Plain Paper, Thin Paper, Thick Paper, Thicker Paper, Recycled Paper, Non carbon paper,Receipt, Business Card, Plastic Card Media Weights and Thickness ADF 51.8 - 128 gsm Paper 0.08 ~ 0.14mm

Long Paper 5000mm (300dpi 1-sided single paper)

Card Slot

1 Plastic Card (Portrait) Without Emboss (0.76-1.02mm) or Embossed (1.24mm)

Media/ Plastic Card Size Width (ISO) - 53.98mm (Min/Max 51-55mm), Length (ISO) - 85.60mm (Min/Max 80.825-90.375mm)

Security Features

Kensington Lock

Interface Lock USB Host **Firmware Updates**^{2,8} Yes

Consumables and Accessories **Carton Contents** ADS machine, USB Type-C Cable, Quick setup guide, Product safety guide, Warranty

Replacement Separation Pad SP-2001C 10,000 sheet

Replacement Pickup Roller PUR-2001C 100,000 sheet **Optional A3 Carrier Sheet** CS-A3301 500 times (Pack of 2)

Optional Output Tray OT-1001C

Optional Legacy Kit AC Adapter with barrel connector, USB Cable (Type-C – Type-A): LK-1001CUK, LK-1001CEU Optional USB-C Power Adapter USB Type-C AC Power Adapter: PA-AD-004UK, PA-AD-004EU

Dimensions and Weights

With Carton Dimension 369 (W) x 158 (D) x 200 (H) mm

Weight 1.70 kg Without Carton Dimension

Input Tray Closed 288(W) x 101(D) x 85(H) mm Input Tray Extended 288(W) x 211(D) x 205(H) mm

Weight

1.37kg

Environment

Power Requirements AC:100-240V, 50/60 Hz, DC: 5V, 3A USB: DC5V, 3A(Type-C) Sound Power Level (Scanning) 62dB

RoHS Yes

GS Mark (Germany) Yes

Power Consumption (Scanning) AC:~11 W, DC:~9 W (Ready) AC:~5 W, DC:~4 W (Sleep) AC:~1.3 W, DC:~1 W (Off) ~0.1W

Power Saving Mode

This enables the scanner to consume less energy when not in use

Operating Environment Humidity 20 - 80 % 5°C - 35°C 41°F - 95°F

Storage Environment

Humidity 10 - 90 % 0°C - 40°C 32°F - 104°F

1 Maximum number of scanned pages per month can be used to compare design durability between like Brother products. For maximum scanner life, it is best to choose a scanner with a duty cycle that far exceeds your scan requirements

- 2 Download from the Brother Solutions Centre http://solutions.brother.com
- 3 All supported using downloadable software
- 4 Capacity varies dependent on paper weight.
- 5 Windows Only
- 6 Windows & macOS
- 7 Windows server support scanner driver

Brother

arth

- 8 Document sizes larger than A4, but not exceeding A3, can be scanned (single-side) using carrier sheet
- 9 300dpi only
- 10 Requires USB Type-C connection with 15W power source (not included)
- 11 For more information visit https://setup.brother.com





At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth. www.brotherearth.com All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

