

Mains Adapter

00223614 Universal Switchable Power Supply Unit, Adjustable, 1000mA, 12W, max. 12V, 8



Highlightstext:

- Plug-in power supply unit for electronic devices with DC voltage input, e.g. portable CD player, radio, light chains, children's toys, digital photo frames, tools, routers, desk lamps and also battery-operated devices, ideal as a replacement or second power supply unit
- Automatic overload and overheating protection as well as short-circuit protection helps safeguard connected devices
- Whether it's plus or minus: Reversible polarity gives you flexibility depending on the requirements of your electronic device
- LED function indicator: The pilot light shows whether the power supply is getting electricity
- 100 - 240 V mains connection suitable for worldwide use in conjunction with country-specific adapter
- Low energy consumption in standby mode
- Adjustable power supply unit with high efficiency: 12 W/max. 1000 mA across all voltage ranges 3V / 4.5V / 5V / 6V / 9V / 12V
- Settings can be made using the voltage selector switch
- With 8 adapter plugs:
- 2 jack plugs: 2.5 and 3.5 mm
- 6 DC plugs: 0.75 x 2.35 / 1.0 x 3.0 / 1.3 x 3.5 / 1.7 x 4.0 / 2.1 x 5.0 / 2.5 x 5.5 mm

Technical characteristics:

- Colour: Black
- Product Division: HiFi, TV & Home Cinema
- Shade of colour: Black
- Connection: Euro Plug
- Output Voltage: 12 V/3 V/4,5 V/5 V/6,0 V/9 V
- Protection circuit: Overload Protection/Overtemperature Protection/Short circuit protection
- Display: LED-Funktion
- Model: Universal Mains Adapter, Stabilized
- Power supply voltage setting: Automatic
- Type: Universal Power Supply
- Max. Output Current: 1 A
- Max. Output Power: 12 W

Delivery:

- 1 switching power supply unit
- 8 adapter plugs
- 1 operating manual

 4 047443 487254	Brand	Item-no.	VE	MB	Quanti
	hama	00223614	6	1	1