



Acer XL Serie

Acer XL2530 (Vero)

The laser projector for every requirement



- Light technology: Laser diode
- Resolution: 1080p Full HD (1,920 x 1,080 px)
- Brightness: 4,800 (standard), 3,600 (eco) ANSI Lumens
- Contrast: 50,000:1
- Life (hr.): 20,000 (standard), 30,000 (eco) hours
- Warranty: 2 years PickUp service, 1 year for the lamp, 5 years for the DLP Chip



Laser Lamp Life



Auto Portrait



24/7 Operation



Built-in Speaker



HDMI 3D



I/O Power On



Acer XL2530 (Vero)

SPECIFICATIONS



Ordering Information

Model	XL2530 (Vero)
Part Number	MR.JWS11.001
EAN	4711121610509

Technical Specifications

Projection technology	DLP 3D Ready & HDMI 3D
DLP Chip	0.65" BrilliantColor™
Version	DarkChip™ 3 DMD
Resolution	1080p Full HD (1,920 x 1,080 px)
Display Format	16:9 (native) / 4:3 (supported)
Contrast	50,000:1
Displayable Colours	1.07 Billion Colors
Brightness	4,800 (standard), 3,600 (eco) ANSI Lumens
Focus / Focal distance	F = 2.50 ~ 2.67 / F = 21.86 ~ 24.00 mm
Projection size (diagonal)	0.71 ~ 7.62 m
Projection distance	1.00 ~ 9.80 m
Throw ratio	1.48 ~ 1.62:1
Zoom / Digital-Zoom	1:1.1x / 2x
Image Offset	132 % %
Horizontal / Vertical frequency	15 ~ 100 kHz / 24 ~ 120 Hz
Projection Modes	360° Projection
Light technology	Laser diode
Life (hr.)	20,000 (standard), 30,000 (eco) hours
Keystone Correction	+/- 40° (vertical) manual
Speaker	1x 15 watts (speaker)
Weight / incl. packaging (kg)	2,9 kg
Dimensions / Shipping dimensions (mm)	286 x 216 x 115.5 mm / 400 x 158 x 280 mm
Power Consumption	210 (standard), 145 (eco), < 0.5 Watt (standby)
Noise level	26 (eco) dB
Uniformity (%)	75 %
Color	white

Input Ports

HDMI with HDCP	2x 1.4b
----------------	---------

Output Ports

USB Type A	1x DC out 5V
Audio out (3.5 mm)	1x

Network and Control Ports

RS232	1x
-------	----

Included Accessory

Power adapter IEC 320 C13	1x (Euro)
HDMI cable	1x 1.8 m
IR remote control	1x
Lens cap	1x
Carrying case	1x
Quick Start Guide	1x

Optional Accessory

Universal ceiling mount short	4713147892877 / MC.JLC11.002
Universal ceiling mount long	4713147892884 / MC.JLC11.003

Warranty

Warranty	2 years PickUp service, 1 year for the lamp, 5 years for the DLP Chip
----------	-----------------------------------------------------------------------

Projection Distance Calculator

Projection Distance Calculator	https://www.acer.com/ac/de/CH/content/acer-projection-calculator
--------------------------------	-------------------------------------------------------------------------------------------------------------------------------------------------



Acer XL2530 (Vero)

APPROPRIATE ACCESSORIE (NOT INCLUDED IN DELIVERY)

Installation



Easily mount your projector to the ceiling with 360° rotation and up to 25° tilt.

Installation



Easily mount your projector to the ceiling with 360° rotation and up to 25° tilt.



Acer XL2530 (Vero)

ACCESSORIES AND FEATURES

Post-Consumer-Recycled Plastik

Recycled plastic (PCR) is used in the manufacture of the projector. This has been recycled to support Acer's efforts to reduce global waste.



Original 24p

Experience true cinema at 24 frames per second. The Acer Blu-Ray projector reproduces films in the original cinema format as they were shot on the film set. See 24p movies through the eyes of the director.



360° Projection

The 360° projection offers you highest flexibility and allows you to use the projector in all positions as well as to realize interesting installations. For example, you can project from the deck of the room onto the floor or a table, or mount the projector on its side to project upright.



360 degree projection

Auto Portrait Mode

With the Auto Portrait mode you will experience the optimal adjustment of the projection to your smartphone. The Auto Portrait mode ensures that content is displayed in 16:9 format without annoying borders. Even when you rotate the smartphone, the picture is automatically adjusted so that you always have an optimal picture.



Auto Portrait

24/7 Operation

This projector promises maximum reliability and delivers a brilliant image even in 24/7 continuous use.*Especially for signage applications, but also for exhibitions in museums or similar, this projector can be used without any worries.* Acer recommends that the projector is switched to standby mode for 30 minutes every 7 days.



24/7 Operation

Customizable startup screen

The Customizable Startup Screen allows you to create an individual startup screen per screenshot. This startup screen, no matter if it is the business user's company logo or a home user's favorite photo, is automatically displayed when the projector is started.



CUSTOMIZABLE STARTUP SCREEN

Acer Football Mode

Bring the stadium to your home with Acer Football Mode. The mode automatically adjusts image brightness, saturation, sharpness and gamma to make skin tones more vivid and greens more vivid. Ideal for football fans and sports enthusiasts.



Football Mode

Auto Shutdown

The Auto Shutdown function automatically shuts down the Acer projector, if no input signal is received after a preset time. This function can be set individually via the menu and helps to save power and lamp hours.



AUTO SHUTDOWN

Instant Pack

InstantPack guarantees the lamp safety of Acer ColorBoost projectors. The current lamps from renowned manufacturers such as Osram and Philips are not damaged in the event of a sudden loss of power. (Acer recommends that the projector be powered until the fan stops) The lamp warranty is 1 year with no hour limit.



INSTANT PACK

HDMI 3D

HDMI 3D: The integrated HDMI 1.4a standard allows 3D content to be transferred from suitable playback devices such as 3D Blu-ray players, 3D set-top boxes and 3D game consoles without the need for an additional PC. For example, Acer 3D shutter glasses Bluray 3D movies and 3D TV shows can be viewed in your living room up to 7.62 meters (300") diagonal.



HDMI Power On

With the HDMI Power On function, the projector is able to turn on automatically when the projector receives a signal via HDMI or VGA. You no longer need to start the projector separately, but can simply switch on your notebook, receiver or game console and the projector will automatically switch on as well.



I/O Power On