

DMC-700SC, DMC-810SC Media Converters

DMC-700SC Media Converter: This converter converts 1000BASE-T Gigabit twisted-pair signals to 1000BASE-SX Gigabit multi-mode fiber signals. Maximum fiber cable distance is 550m. 1 RJ-45 twisted-pair port and 1 fiber port (SC type connector) are provided.

DMC-810SC Media Converter: This converter converts 1000BASE-T Gigabit twisted-pair signals to 1000BASE-LX Gigabit single-mode fiber signals. Maximum fiber cable distance is 10km. 1 RJ-45 port and 1 fiber port (SC type connector) are provided.

Media Converter Features

- One-channel media conversion between 1000BASE-T and 1000BASE-SX/LX
- Auto negotiation of duplex mode on twisted-pair port
- Auto MDI-II/MDI-X for twisted-pair port
- Full wire-speed forwarding rate
- Front panel status LEDs
- Can be used as a stand-alone device or with chassis -
- Hot-swappable when used with chassis

Technical Specifications

LED Indicators

- Power (PWR) - LINK/ACT
- Housing Dimensions
- 120 x 88 x 25 mm

Power Input

- 7.5V 1.5A
- Through external AC power adapter

Operating Temperature

0° - 40°C

Storage Temperature

-25° - 70°C

Humidity

10 ~ 90% non-condensing

Emission (EMI)

- FCC Class B
- VCCI Class B
- CE Class B
- C-Tick



ACN 052 202 838

D-Link®

Specifications subject to change without prior notice.
D-Link is a registered trademark of D-Link Corporation/D-Link System Inc. All other trademarks belong to their proprietors.

U.S.A.	TEL: 1-949-788-0805	FAX: 1-949-753-7033	www.dlink.com
Canada	TEL: 1-905-8295033	FAX: 1-905-8295095	www.dlink.ca
Europe	TEL: 44-20-8731-5555	FAX: 44-20-8731-5511	www.dlink.co.uk
U.K.	TEL: 44-20-8731-5555	FAX: 44-20-8731-5511	www.dlink.co.uk
Germany	TEL: 49-6196-77990	FAX: 49-6196-7799300	www.dlink.de
France	TEL: 33-1-30238688	FAX: 33-1-30238689	www.dlink-france.fr
Benelux	TEL: 31-40-2668713	FAX: 31-40-2668666	www.dlink-benelux.nl
Italy	TEL: 39-02-2900-0676	FAX: 39-02-2900-1723	www.dlink.it
Iberia	TEL: 34-93-4090770	FAX: 34-93-4910795	www.dlinkiberia.es
Sweden	TEL: 46-(0)8564-61900	FAX: 46-(0)8564-61901	www.dlink.se
Norway	TEL: 47-22-991890	FAX: 47-22-207039	
Denmark	TEL: 45-43-969040	FAX: 45-43-424347	www.dlink.dk
Finland	TEL: 358-9-622-91660	FAX: 358-9-622-91661	www.dlink-fi.com
Singapore	TEL: 65-774-6233	FAX: 65-774-6322	www.dlink-intl.com
Australia	TEL: 61-2-94177100	FAX: 61-2-94171077	www.dlink.com.au
Japan	TEL: 81-3-5434-9678	FAX: 81-3-5434-9868	www.dlink.co.jp
China	TEL: 86-10-8809-7777	FAX: 86-10-8809-6789	
India	TEL: 91-22-652-6696	FAX: 91-22-652-8914	www.dlink-india.com
Middle East	TEL: 202-6356176	FAX: 202-6356192	www.dlink-me.com
South America	TEL: 56-2-232-3185	FAX: 56-2-232-0923	www.dlink.cl
South Africa	TEL: 27(0)126652165	FAX: 27(0)126652186	www.d-link.co.za
Russia	TEL: 7-095-737-3389	FAX: 7-095-737-3390	www.dlink.ru
Taiwan	TEL: 886-2-2910-2626	FAX: 886-2-2910-1515	www.dlinktw.com.tw
D-Link Corp.	TEL: 886-2-2916-1600	FAX: 886-2-2914-6299	www.dlink.com.tw



RECYCLABLE
Rev. 01 (Jan. 2002)
Printed in Taiwan