

## Power Strip

00223160 Power Strip, 6-Way, Overvoltage Protection Switch, 90°, Indiv. Switchable, 1.4 m, blk



### Highlightstext:

- Multi-socket power strip for connecting up to six individually switchable electrical devices
- Individual switching on and off: six illuminated switches, ideal for PC and HiFi components or the workshop
- Integrated voltage surge protection protects against voltage peaks, static charges and indirect lightning strikes
- Red pilot light: optical function display for the voltage surge protection
- For hanging: integrated hanging eyelets for wall mounting
- Socket inserts rotated by 90°: no sockets are covered, ideal for angled plugs, large earthed plus and power supply units
- Larger distances between the individual sockets are ideal for power supply units
- With increased touch protection to avoid accidental contact
- On/Off switch illuminated in red, ideal for switching off not-needed or standby equipment
- 6 earthed contact sockets

### Note for Consumers:


If the red pilot light on the overvoltage protection does not light up after being switched on, the overvoltage protection is no longer intact. Connected devices are no longer protected.

### Technical characteristics:

- Colour: Black
- Product Division: HiFi, TV & Home Cinema
- Shade of colour: Black
- Connection: Socket with Earth Contact
- Mains Specification: 16 A
- Maximum Connected Load: 3680 W
- Maximum leakage current: 6000 A
- Operating Voltage: 250 V
- Type of Cable: H05VV-F3G1,5
- maximum total leakage: 18000 A
- Additional Functions: Surge Protection
- Function: Standard, Switch
- Material: Plastic Material
- Number of Sockets: 6
- Number of Wires: 3
- Cable Length: 1.4 m
- Width x Depth x Height: 7.5 x 4.5 x 46 cm
- Wire Cross-Section: 1.5 mm<sup>2</sup>

### Delivery:

- 1 power strip
- 1 instruction manual

 4 047443 480378	Brand	Item-no.	VE	MB	Quanti
	hama	00223160	15	1	1