

## Lamps

00176602 WLAN LED Lamp, E14, 5.5W, Dimmable, Candle, for Voice / App Control, white



### Highlightstext:

- Smart light control with the WLAN LED lamp in candle shape: create illumination, effect lighting or special lighting ambiances easily with app or voice control, e.g. dim or change the colour temperature
- Our WLAN light bulb works without any gateway (hub): you don't need an additional device, and you save on extra costs since the WLAN lamp establishes a direct WiFi connection with the router
- From cosy to active: choose exactly the colour temperature that matches your activities, e.g. warm white for a relaxed evening or daylight for cooking
- Step by step to the Smart Home: with the Hama Smart Home app, you can expand and network your smart home with any number of Hama Smart Home products
- Be it on the sofa or the train: with the Hama Smart Home app, you can control your WLAN LED lamp from anywhere and you have control over your lighting at all times
- Whether it be Amazon Alexa or Google Assistant: conveniently control all kinds of lighting effects via the smart lamp using voice commands
- Simple installation on your own WiFi network: since no hub is required, your devices can be set up in just a few minutes
- High compatibility: works with Amazon Alexa, Google Assistant, Siri Shortcuts, Home Connect Plus, iOS and Android. Can also be connected to all Alexa and Google Assistant-compatible smart home products from other manufacturers
- Timer control: you define in the app when the WLAN bulb is to switch on and off, for example
- With the devices integrated into your WLAN, groups or scenes can be created, e.g. the smart LED lamp can be linked to a motion detector
- This means that you can save energy with the targeted control of your lighting including - usefully - while out and about, if you have forgotten to switch the light off. That's because you are always kept up to date about the current status via the app or push notification
- Your data is stored exclusively on German servers

### System Requirements:

- Operating system: Android 4.4 and iOS 8.0 or later

### Note for Consumers:

An optional expansion enables control of the devices via Amazon Alexa or Google Assistant (both sold separately).

### Amazon Alexa:

the required Alexa skill "Hama Smart Home" must be activated in the Alexa app. The user account for the Hama Smart Home app is then connected to Alexa.

This allows the devices to be controlled via voice control (e.g. switch On/Off, stepless dimming, change colour temperature).

### Google Assistant:

the "Hama Smart Home" service must be activated in the Google Home app for this. The user account for the Hama Smart Home app is then connected to Google.

This allows the devices to be controlled via voice control (e.g. switch On/Off, stepless dimming, change colour temperature).

### Technical characteristics:

- Colour Reproduction Index RA (min.): 80
- Light Colour: Warm white to daylight
- Signal Transmission: WiFi
- Beam angle: 200 °
- Bluetooth Version: 4.2
- Colour Consistency: 2.9


## Lamps

00176602 WLAN LED Lamp, E14, 5.5W, Dimmable, Candle, for Voice / App Control, white

- Colour-tuneable light source: Yes
- Connected light source (CLS): Yes
- EAR Reg.No.: DE 38720470
- Energy Efficiency Class (A to G): F
- Energy consumption in on-mode: 6 kWh/1000h
- Flicker for LED and OLED MLS: 1 <
- Frequency: 50 Hz
- Frequency Band: 2,4GHz
- L70B50 lifetime for LED and OLED light sources: 20000 h
- Light source: Non-directional
- Lighting technology used: LED Lamp
- Lumen maintenance factor (LED/OLED): 95 %
- Networked standby power (Pnet): (connected light source): 0.5 W
- Operating Voltage (AC): 230 V
- R9 colour rendering index value: 11
- Radiated max. transmission power: 0.1 W
- Shift factor for Pon (min.): 0.5
- Standby power (Psb): 0.5 W
- Stroboscopic effect for LED and OLED MLS: 0.9
- Survival factor (for LED and OLED): 0.9
- Useful luminous flux (360): 470 lm
- Can be Dimmed: No
- Colour Temperature: 2700 - 6500 K
- Cooling Element/Housing: Plastic Coated Aluminium
- Design / Diameter / Height: Candle / 37 mm / 106 mm
- Dimming: App/Speak
- IP protection class: IP20 (Dry Rooms)
- Lamp socket: E 14
- Operating Position: 360 °
- Optimal Ambient Temperature: 25 °C
- Power Consumption of an Equivalent Incandescent Lamp: 40 W
- Voice Assistant: Amazon Alexa/Google Assistant
- Net Weight: 25 g
- Lamp Current: 48 mA
- Recommendations for Recycling: Recycling Depot or Collection Point
- App Control: Hama Smart Home
- Bulb Serves as Replacement for Standard Bulbs of This Size: Candle
- Recommended Use: Home Assistant
- Suitable for Accent Lighting: No - Beam Angle between 120° and 360° (use)

### Delivery:

- 1 WiFi LED lamp
- 1 quick reference guide

 4 047443 469304	Brand	Item-no.	VE	MB	Quanti
	<b>hama</b>	00176602	10	1	1