



Active holder for fixed installation

With tilt swivel. 2A charging. 12/24V. With Easy-switching system. Charging via pogo pins.

Item no: 713321

EAN Number: 7320287133219

An active holder which is to be connected inside the dashboard, this gives a discreet, neat installation without cables hanging over the interior!

You can choose to use the holder as an active holder for charging of your device only, or to connect an adapter to the Molex connector for additional features. Then you can use the holder also for power supply of a GPS receiver or other own solutions (can not be used for data communication or audio connection).

12/24 Volt. The product is E-approved. Connect the power cable with a 2 A fuse. 2 A charger. Professional installation recommended. The holder is attached onto a tilt swivel so you can easily adjust your device in order to avoid light reflection. Attach onto a ProClip Mounting Platform.

Easy-switching system:

The easy-switching system enables you to upgrade the holder only, and keep the installed cables. It saves you a lot of time! When upgrading to a new device, you do not longer need to make a full installation. Same goes for maintenance in case of warranty or damage. You simply disconnect the holder from the charging cable via the Molex 6-pin quick connector, and then connect the new holder. The switch is done in a few seconds.

Fits the following models:

Honeywell CT45 Honeywell CT45 XP

For a complete list, see www.brodit.com/en/product/713321

Measurements:

Height 110 mm Width 82 mm Depth 65 mm Volume 586 cm³ Weight 239 g

Charging specifications:

Input voltage: DC/10-30V Charging voltage: DC/4.75-5.3V Output current(Typ): 2.0A Input & output protection: Input polarity reversal/Output over voltage/Output over current/Output short protection LED charging indicator: Power input indicator(Green), Ovp/Ocp/Output short (Red)

Operating temperature: 0°C ~ +40°C Storage temperature: -20°C ~ +80°C

RoHS compliant: ROHS

BRODIT.COM GENERATED 08-12-2025