

## Lenovo Go Wired Speakerphone

The **Lenovo Go Wired Speakerphone** brings enterprise-grade conferencing and audio to the remote workforce. In one portable plug-and-play solution, you can hold natural conference calls optimized by advanced voice-first algorithms. And with Teams Certified<sup>1</sup> tech, you can rest easy knowing you can make the most of your favorite UC platform.

Lenovo  
Go



Enterprise  
Conferencing.  
Remote-First  
Design.

Lenovo

# Lenovo Go Wired Speakerphone



Thunder Black

Storm Grey

## WHY CHOOSE THE LENOVO GO WIRED SPEAKERPHONE?



### Enterprise-Quality Audio

The Microsoft Teams certified<sup>1</sup> Lenovo Go Speakerphone punches above its weight with two voice-enhancing omni-directional mics engineered for consistent, reliable audio. And with cutting-edge environmental noise cancelling, acoustic echo control, automatic gain control, beamforming, and wide-band processing, it delivers a conferencing experience that's as good as the real thing.



### Designed for On-The-Go

Be ready to rock even a last-minute meeting with the Lenovo Go Wired Speakerphone's portable plug-and-play capabilities and effortless PC UC support that enables immediate access to media and conferencing. When duty calls, the clever design of the speaker allows you to neatly tuck the cable away under the base and hit the road fast.



### Intuitive Control Panel

Designed to be simple, the Lenovo Go Wired Speakerphone's in-built control panel is packed with intuitive features such as a dedicated Teams button, smooth volume wheel, tactile response control buttons, and LED hairline indicators that effortlessly guide even first-time users.

## SPECIFICATIONS

### PERFORMANCE

#### Speaker

Driver Units	: $\Phi$ 40 x 20.8 mm
Frequency Range	: 140 Hz - 20 kHz
Impedance	: 4 $\Omega$
Rated Power	: 3W
Sensitivity (SPL)	: >85 dB @1W/0.5m

#### Microphone

Microphone	: 2 x Omni-direction Microphones
Frequency	: 100 Hz - 10 kHz
SNR	: 64 dB(A)

#### General

Power Rating	: 5V/1A
LED Indication	: Teams Event Call Status Microphone Mute Volume Range

Audio Performance	: ENC (Environmental noise cancellation) AEC (Acoustic echo cancellation) Automatic Gain Control Double Talk Beamforming
-------------------	--

### DESIGN

#### Packed Dimensions

mm	: 129 x 125 x 89
inches	: 5.08" x 4.92" x 3.50"

#### Unpacked Dimensions

mm	: $\Phi$ 90 x 49
inches	: $\Phi$ 3.54" x 1.93"

#### Weight

Speakerphone	: Starting at 265 g (0.58 lbs)
--------------	--------------------------------

#### Packed

Speakerphone	: Starting at 447 g (0.99 lbs)
--------------	--------------------------------

#### Colors

Thunder Black
Storm Grey

### CONNECTIVITY

#### Interface

USB-C, USB-A Adapter

#### Cable Length

79 cm

### INFORMATION

#### Certification

Certified for Microsoft Teams<sup>1</sup>,  
Compatible with Skype™ for Business

#### Ship Group (What's in the Box)

Lenovo Go Wired Speakerphone  
Lenovo USB-C (Female) to USB-A (Male)  
Adapter  
Travel Pouch  
Start Manual  
Warranty Posters

#### Warranty

1 Year

#### Part Numbers (PN)

**Commercial (Thunder Black Color)**  
4XD1C82055

#### Consumer (Storm Grey Color)

GXD1C82051

<sup>1</sup> Lenovo Go Wired Speakerphone is certified for Microsoft Teams at time of availability.



[WWW.LENOVO.COM/GO](http://WWW.LENOVO.COM/GO)

Lenovo reserves the right to alter product offerings and specifications at any time, without notice. Lenovo makes every effort to ensure accuracy of all information but is not liable or responsible for any editorial, photographic, or typographic errors. All images are for illustration purposes only. For full Lenovo product, service, and warranty specifications, visit [www.lenovo.com](http://www.lenovo.com). Lenovo makes no representations or warranties regarding third-party products or services. **Trademarks:** The following are trademarks or registered trademarks of Lenovo: Lenovo, the Lenovo logo, Rescue and Recovery, ThinkPad, ThinkCentre, ThinkStation, ThinkServer, ThinkVantage, and ThinkVision. Other company, product, and service names may be trademarks or service marks of others. Battery life (and recharge times) will vary based on many factors, including system settings and usage. Visit [www.lenovo.com/lenovo/us/en/safecomp/](http://www.lenovo.com/lenovo/us/en/safecomp/) periodically for the latest information on safe and effective computing. ©2021 Lenovo. All rights reserved.