



4 Port HDMI 4K60, USB 2.0 & Audio KVM Switch

No.: 39308

Switch between 4 HDMI equipped PCs from one keyboard, mouse and monitor

Description

- Controls four HDMI equipped PC's from a single keyboard, mouse and monitor
- Switch via the unit's push buttons or keyboard hot keys
- Supports HDMI signals, up to 4K 60Hz with 4:4:4 8bit
- Independent audio switching and 2 ports USB 2.0 Hub for sharing additional USB peripherals
- 2-year warranty

A KVM switch allows an operator to conveniently control and manage multiple devices, such as PCs and servers, from a single keyboard, mouse and display console.

The Lindy 4 Port HDMI 18G & USB KVM Switch Pro is a reliable, complete solution for the control of four host PC's using a single keyboard, mouse & HDMI display.

Support for resolutions up to 4K Ultra HD 60Hz ensures the highest image quality, perfect for demanding graphical content in gaming setups, video editing or quad system control workstations. The audio output ports on the main unit also allow users to connect headphones or speakers to add immersive 2CH audio and a microphone. Additional USB peripherals can be integrated with the 2 port USB 2.0 hub. Both audio and USB hubs can be switched independently of the PCs allowing users to print from one PC whilst working on another for example.

It supports True Transparent USB switching, an advanced USB emulation technology that allows the KVM to recognise specific keyboard & mouse models and emulate any of their associated special key and function information. This also provides enhanced support for combined use with KVM extenders.

The KVM switch features multiple switching options including push buttons on the unit and configurable hotkeys that provide simple, reliable control for the user, great for both professional and first time users.

Please Note: connection cables are not included.

Technical details

Specifications:

- AV Interface: HDMI
- Console Interfaces: USB

- Interface Standard: HDMI 2.0, USB 2.0
- Maximum Resolution: 3840x2160@60Hz
- HDCP Support: 1.4 & 2.2
- Supported Audio: Analogue Stereo
- Separate Audio Ports: 3 x 3.5mm (Female)
- Serial Interface: -
- Console Number: 1
- Max Number PC/Server: 4
- Cascadable: -
- Switching Method: Push Button / Configurable Hotkeys
- 19" Rack Mountable: -
- Special Features: 3 Port Shared USB Hub, Independent audio and Hub switching, Active LED Indicators

Connectors:

- Console Interfaces:
 - HDMI Type A (Female)
 - 4 x USB Type A (Female)
 - 2 x 3.5mm (Female)
- PC/Server Interfaces:
 - 4 x HDMI Type A (Female)
 - 4 x USB Type B (Female)
 - 8 x 3.5mm (Female)
- Other Interfaces: -
- Power: 5.5/2.1mm DC socket

Physical Properties:

- Dimensions (approx.) WxDxH: 255x117.5x45mm (10.04x4.63x1.77in)
- Housing Material: Metal
- Net Weight: 0.97kg (2.14lb)
- Operating Temperature: 0°C - 40°C (32°F - 104°F)
- Storage Temperature: -20°C - 60°C (-4°F - 140°F)
- Humidity: 0 - 90% RH (non-condensing)
- Power Requirements: 9VDC 2A
- Colour: Silver

Miscellaneous:

- Packaging Type: Carton box
- Packaging Dimensions: 315x65x215mm (12.4x2.56x8.46in)
- Gross Weight: 1.154kg (2.54lb)
- Warranty (Years): 2
- Certificated: CE, FCC, RoHS & REACH

Package Contents:

- 4 Port HDMI 18G KVM Switch
- Multi-country PSU (UK, EU, US, AUS)
- Lindy Manual

Purchasing Information:

- No.: 39308
- EAN: 4002888393089