

Mains Adapter

00223613 Universal Switchable Power Supply Unit, Adjustable, 1000mA, 12W, max. 12V, 7



Highlightstext:

- Plug-in power supply unit for electronic devices with DC voltage input, e.g. portable CD player, radio, light chains, children's toys, digital photo frames, tools, routers, desk lamps and also battery-operated devices, ideal as a replacement or second power supply unit
- Automatic overload and overheating protection as well as short-circuit protection helps safeguard connected devices
- Whether it's plus or minus: Reversible polarity gives you flexibility depending on the requirements of your electronic device
- LED function indicator: The pilot light shows whether the power supply is getting electricity
- 100 - 240 V mains connection suitable for worldwide use in conjunction with country-specific adapter
- Low energy consumption in standby mode
- Adjustable power supply unit with high efficiency: max. 12W/max. 1000 mA across all voltage ranges 3V / 4.5V / 5V / 6V / 7.5V / 9V / 12V
- Settings can be made using the switch key
- With 7 adapter plugs:
 - 2 USB adapters: 1x micro-USB plug, 1x USB-A socket
 - 5 DC plugs: 1.35 x 3.5/1.7 x 4.0/2.1 x 5.0/1.5 x 5.5/2.5 x 5.5 mm

Technical characteristics:

- Colour: Black
- Product Division: HiFi, TV & Home Cinema
- Shade of colour: Black
- Connection: Euro Plug
- Mains Connection: Euro Plug
- Input Voltage Range from/to: 100-240 V
- Output Voltage: 12 V/3 V/4,5 V/5 V/6,0 V/7,0 V/9 V
- Protection circuit: Overload Protection/Overtemperature Protection/Short circuit protection
- Display: LED-Funktion
- Model: Universal Mains Adapter, Stabilized
- Power supply voltage setting: Manual
- Type: Universal Power Supply
- Weight: 167 g
- Max. Output Current: 1 A
- Max. Output Power: 12 W

Delivery:

- 1 switching power supply unit
- 7 plugs
- 1 switch key
- 1 operating manual

 4 047443 486226	Brand	Item-no.	VE	MB	Quanti
	hama	00223613	6	1	1