

Wireless Switch Modul

00176556 WiFi Retrofit Switch for Lights and Sockets, Flush Installation



Highlightstext:

- Turns your existing ceiling light into a WiFi light or a socket into a wireless socket, allowing operation via an app or voice control
- Lights: The module is connected to your light's power supply, which can be in the cabling behind the existing light switch, in a junction box or at the base of the light
- Sockets: The module is mounted behind the socket
- Can be used for all switch systems since the existing switch is retained
- WiFi module for integration into your own WiFi network via the free "Hama Smart Home" app
- Control via free app or optionally via "Amazon Alexa" and "Google Assistant" voice control
- Also controllable on the move via the app, keeping you in full control
- High compatibility: works with Amazon Alexa, Google Assistant, Siri Shortcuts, Home Connect Plus, iOS and Android. Can also be connected to all Alexa and Google Assistant-compatible smart home products from other manufacturers
- Supports timed control
- Works without gateway/bridge
- No dimming function

System Requirements:

- Operating system: Android 4.3 and iOS 8.0 or later

Note for Consumers:

Installation only by a qualified electrician.

Amazon Alexa:

the required Alexa skill "Hama Smart Home" must be activated in the Alexa app. The user account for the Hama Smart Home app is then connected to Alexa.

This allows the devices to be controlled via voice control (switching on/off).

Google Assistant:

the "Hama Smart Home" service must be activated in the Google Home app for this. The user account for the Hama Smart Home app is then connected to Google.

This allows the devices to be controlled via voice control (switching on/off).

Technical characteristics:

- Product Division: Home & Living

- Signal Transmission: WiFi

- Frequency Band: 2,4GHz

- Mains Frequency: 50 Hz

- Max. Performance: 2300 W

- Operating Voltage: 230 V

- Radiated max. transmission power: 0.06 W

- Can be Dimmed: No

- Voice Assistant: Amazon Alexa (AVS), Apple Siri (Shortcuts), Google Home

- W x H x L: 4.7 x 1.7 x 5.2 cm

- Max. Output Current: 10 A

- App Control: Hama Smart Home

- Recommended Use: Home Assistent



Wireless Switch Modul

00176556 WiFi Retrofit Switch for Lights and Sockets, Flush Installation

Delivery:

- 1 WiFi retrofit switch
- 1 quick reference guide

| | Brand | Item-no. | VE | MB | Quanti |
|-----------------|-------|----------|----|----|--------|
| | hama | 00176556 | 10 | 1 | 1 |
| 4 047443 405203 | | | | | |